

## KRD6-4

Interruttore differenziale, 4P



|               |                             |                |          |          |       |           |
|---------------|-----------------------------|----------------|----------|----------|-------|-----------|
| [Hz]<br>50    | [mm <sup>2</sup> ]<br>do 35 | [°C]<br>-25÷40 | IP<br>20 | <br>4P   | <br>4 | <br>TH 35 |
| Ui [V]<br>400 | CE                          | EAC            | VDE      | UK<br>CA |       |           |



KRD6-4/25/30

|                 | [V]                 | In [A] | I <sub>Δn</sub> [mA] | Tipo di protezione differenziale |   |
|-----------------|---------------------|--------|----------------------|----------------------------------|---|
| KRD6-4/25/30    | <b>23183</b> 400 AC | 25     | 30                   | AC                               | 4 |
| KRD6-4/40/30    | <b>23184</b> 400 AC | 40     | 30                   | AC                               | 4 |
| KRD6-4/63/30    | <b>23185</b> 400 AC | 63     | 30                   | AC                               | 4 |
| KRD6-4/25/30-A  | <b>23191</b> 400 AC | 25     | 30                   | A                                | 4 |
| KRD6-4/40/30-A  | <b>23192</b> 400 AC | 40     | 30                   | A                                | 4 |
| KRD6-4/63/30-A  | <b>23193</b> 400 AC | 63     | 30                   | A                                | 4 |
| KRD6-4/100/30   | <b>23197</b> 400 AC | 100    | 30                   | AC                               | 4 |
| KRD6-4/100/30-A | <b>23198</b> 400 AC | 100    | 30                   | A                                | 4 |
| KRD6-4/63/300   | <b>23201</b> 400 AC | 63     | 300                  | AC                               | 4 |

L'interruttore differenziale: viene utilizzato per una protezione aggiuntiva contro le scosse elettriche, progettato per funzionare in circuiti AC sinusoidali e circuiti di tipo A sinusoidali in corrente alternata e pulsante con componente diretta. Conformità a: EN61008-1

## KRD6-4

Interruttore differenziale, 4P



KRD6-4/25/30



KRD6-4/40/30



KRD6-4/63/30



KRD6-4/25/30-A



KRD6-4/40/30-A



KRD6-4/63/30-A




KRD6-4/100/30




KRD6-4/100/30-A




KRD6-4/63/300




KRD6-4/25/30



KRD6-4/40/30




KRD6-4/63/30




KRD6-4/25/30-A

## KRD6-4


Interruttore differenziale, 4P




KRD6-4/40/30-A




KRD6-4/63/30-A



KRD6-4/100/30



KRD6-4/100/30-A



KRD6-4/63/300