

BENO ECO

LED- Deckenleuchte



[W] 220-240 AC	[Hz] 50	[°] 110	≥30000	[h] 30000	Ellipse ≤ 6x Mackdam	Ra 80
Hg	SMD			IP 65		°C -20÷45
		[mm²] 0,5÷1,5	0,5m	CE	EAC	UK CA
↓						



BENO ECO 12W CCT O W

	[W]	[lm]	Tc [K]	
BENO ECO 12W CCT O W 38380	12	1200 (WW) 1300 (NW) 1250 (CW)	3000 4000 6500	weiß
BENO ECO 12W CCT O B 38381	12	1050 (WW) 1150 (NW) 1100 (CW)	3000 4000 6500	schwarz
BENO ECO 20W CCT O W 38382	20	1850 (WW) 2000 (NW) 1900 (CW)	3000 4000 6500	weiß
BENO ECO 20W CCT O B 38383	20	1450 (WW) 1600 (NW) 1500 (CW)	3000 4000 6500	schwarz
BENO ECO 30W CCT O W 38384	30	2850 (WW) 3150 (NW) 3050 (CW)	3000 4000 6500	weiß
BENO ECO 30W CCT O B 38385	30	2150 (WW) 2400 (NW) 2300 (CW)	3000 4000 6500	schwarz
BENO ECO 40W CCT O W 38386	40	4050 (WW) 4600 (NW) 4450 (CW)	3000 4000 6500	weiß
BENO ECO 40W CCT O B 38387	40	3800 (WW) 4050 (NW) 3900 (CW)	3000 4000 6500	schwarz

- Gehäusematerial: PP

Erstellt am: 02.08.2024, 14:30

Technische Änderungen vorbehalten. Die in diesem Material enthaltenen Daten sind nicht rechtsverbindlich.

BENO ECO

LED- Deckenleuchte

- Abdeckungsmaterial: PP



BENO ECO 12W CCT O W



BENO ECO 12W CCT O B



BENO ECO 20W CCT O W



BENO ECO 20W CCT O B



BENO ECO 30W CCT O W



BENO ECO 30W CCT O B




BENO ECO 40W CCT O W




BENO ECO 40W CCT O B

BENO ECO


LED- Deckenleuchte




BENO ECO 12W CCT O W




BENO ECO 12W CCT O B




BENO ECO 20W CCT O W




BENO ECO 20W CCT O B




BENO ECO 30W CCT O W



BENO ECO 30W CCT O B



BENO ECO 40W CCT O W



BENO ECO 40W CCT O B