

# Kanlux



## Kanlux MAH MAX

- 5 ani Garanție în conformitate cu prevederile declarației de garanție, disponibile pe site



IP  
65

up to

160  $\frac{\text{lm}}{\text{W}}$

220-240 AC	50	$\geq 25000$	50000	ellipse $\leq 6x$ MacAdam	Ra 80	SMD
		<b>IP</b> 65		$-20 \div 40$		<b>IK</b> 08
	$1 \div 2,5$	0,5m	<b>CE</b>	<b>EAC</b>	<b>UK</b> <b>CA</b>	



MAH MAX 19W 06 NW RYF



MAH MAX 19W 06 NW RYF	<b>38463</b>	19	3050	4000	110	gri
MAH MAX 38W 12 NW RYF	<b>38464</b>	38	6080	4000	110	gri
MAH MAX 48W 15 NW RYF	<b>38465</b>	48	7680	4000	110	gri
MAH MAX 38W12NW RYF B	<b>38469</b>	38	6080	4000	110	negru



MAH MAX 19W 06 NW RYF



MAH MAX 38W 12 NW RYF




MAH MAX 48W 15 NW RYF




MAH MAX 38W12NW RYF


B




MAH MAX 19W 06 NW RYF



MAH MAX 38W 12 NW RYF



MAH MAX 48W 15 NW RYF



MAH MAX 38W12NW RYF

B

Date of issue: 31.10.2024, 15:15

Ne rezervăm dreptul de a face modificări tehnice. Datele conținute în acest material nu sunt obligatorii din punct de vedere juridic.

Fotometrie: rezultatele obținute în timpul testării unui exemplar concret.

RO